

## LED MAP LIGHT













DESIGNED FOR MULTI-SECTOR APPLICATIONS







## **LED MAP LIGHT**

Very low power - only 0.07A


Red & white output

Adjustable arm

Slimline design

Integrated switch









| SPECIFICATION   |     | ALL DIMENSIONS HAVE A TOLERANCE OF +/-1mm |                   |
|-----------------|-----|---|-------------------|
|                 |     | ML2271<br>(12V)                           | ML2271/2<br>(24V) |
| Voltage Range   | VDC | 10-14                                     | 20-28             |
| Average Current | А   | 0.07                                      | 0.035             |
| Light Output    | lm  | 72  | 72                |
| Watts           | W   | 0.85W                                     | 0.85W             |
| Weight          | kg  | 0.2                                       | 0.2               |
| Temp. Range     | °C  | -30 to +40                                | -30 to +40        |
| IP Rating       | IP  | IP40                                      | IP40              |

E & OE

